

## Dante/AES67 25 Watt PoE+ Bass Expander Speaker



The BX-25D is a 25-Watt Dante/AES67 4.5" woofer speaker which allows lower fuller frequencies to be added to any room. Primarily designed for the Aurora ReAX Room to complement the RXT-4D/DV (4" Touch Controller with Dante/AES67 Beamforming Microphone & Speaker). The small form factor and light weight allows it to be mounted under the table with the included mounting brackets or just about anywhere. The mounting bracket has rubber grommets built in to help isolate vibration into the table. It also features an OLED for IP Address and other status information for better setup and serviceability.

### Features:

- 4.5" Woofer 40Hz-2000Hz
- 25-Watt PoE+ Amplifier
- Anti-Magnetic Shielding
- Dante/AES67
- OLED Display with Selection Buttons for Status Information
- Power/Status Indicators
- Internal Web Server for Remote Diagnostics and Settings

### Technical Specifications

Model Name	BX-25D
<b>Technical</b>	
Audio Bandwidth	40Hz – 2000Hz
Speaker Size	4.5" Dia
Shielding	Anti-Magnetic
LAN	RJ-45 10/100/1000M PoE+
Display	OLED for Network Information
Interface	Front Buttons, Web Server
<b>Mechanical</b>	
Housing	Black ABS Plastic
Dimensions (L x W x H)	5.72" x 5.72" x 4.512" (145.36 x 145.36mm x 114.61mm)
Weight	4lbs (1.81kg)
Mounting	Under Table Mount
Power Supply	PoE+
Power Consumption	25.4 Watts
Operation Temperature	0~40° C [32~104° F]
Storage Temperature	-20~60° C [-4~140° F]
Relative Humidity	20~90% RH [No Condensation]
<b>Package Contents</b>	1x BX-25D, 2x Mounting Ears

**Note: Specifications subject to change without notice.**